

IGNITE™ BACK-UP KITS

Most vehicles have very inadequate backup lighting, which can be a major safety problem. Rigid makes it easy to add compact and powerful backup lighting to any vehicle with the Rigid Ignite™ Backup Kit. The Ignite Series Accessory Lights are small but pack a lot of power with 1000 raw lumens in a light that measures just 1.4" x 1.4" x 2". While a wiring harness is not included, the powerful LEDs in each light consume less than one amp each, so powering them is often as easy as tapping into the vehicle's existing backup lighting circuit.



FEATURES


- Small Package, Big Output
- IP68 Compliant
- RIGID Quality & Performance
- Unlimited Mounting Options
- (Surface Mount);
• Mates To Any Go-Pro® Case Mount
- Easy (Flush Mount) Install
- Using 1.75" Hole saw
- Low Minimum Voltage; 6-28 VDC




DIMENSIONS & MOUNTS



SURFACE MOUNT



FLUSH MOUNT



SPECIFICATIONS



	MOUNT	KIT PART NO.	WT. (OZ)	WATTS	AMP DRAW @ 14VDC	LEDs	*RAW LUMENS	BEAM DISTANCE (m)			**PEAK BEAM INTENSITY(cd)
								A	B	C	
HYBRID DIFFUSED	SM	20541	3.8	12	0.48	1	1000	9	29	60	885
	FM	20641	3.8	12	0.84	1	1000	9	29	60	885

A = LUX AT 10 METERS

B = BEAM DISTANCE (m) WITH 1 LUX

C = BEAM DISTANCE (m) WITH .25 LUX

KIT INCLUDES

- 2 Ignite Lights (Surface or Flush Mount)
- 2 Sets of Hardware
- 48" Wire Leads
- 2 Mounting Brackets (Surface)